

TLDR

Quick summary of today's notes. Lecture starts on next page.

- A *linear equation* is an equation that can be written in the form $a_1x_1 + \cdots + a_nx_n = b$ where the a_i 's and b are numbers and the x_i 's are variables. Like $4x_1 + 5x_2 - \pi x_3 = -1$ or $x_1 = x_2 + 3$ or $0 = 0$ or even $0 = 1$, but NOT $x_1^2 + x_2^2 = 1$ or $|x_1| + 3x_2 = 0$ or $\sin(x_1) = \sqrt{2}/2$ or $2^{x_1+x_2} = 4$.
- A *linear system* is a list of linear equations.
- A *solution* to a linear system is a list of values we can assign the variables that make all equations in the system true. Like $(x_1, x_2) = (3, 4)$ is a solution to the linear system with two equations $x_1 + x_2 = 7$ and $x_2 - x_1 = 1$. Two linear systems are *equivalent* if they have the same solutions.
- Any linear system has 0, 1, or infinitely many solutions. If a linear system has two different solutions then it has infinitely many. If a linear system has no solutions then it is *inconsistent*.
- A *matrix* is a rectangular array of numbers like $\begin{bmatrix} \sqrt{2} \end{bmatrix}$ or $\begin{bmatrix} 1.1 & -1.1 \\ 1.1 & 1.2 \end{bmatrix}$ or $\begin{bmatrix} 1 & 7 & -1 \\ 0 & 4 & 3 \end{bmatrix}$.
- A matrix with m rows and n columns is $m \times n$ or “ m -by- n .”
- There are two important matrices associated to a linear system: the *coefficient matrix* and the *augmented matrix*. Best defined by example:

$$\underbrace{\begin{array}{r} 3x_1 + x_3 = 8 \\ x_2 - x_3 = 0 \\ 5x_1 + 4x_2 + 2x_3 = 1 \end{array}}_{\text{linear system}} \rightsquigarrow \begin{array}{c} \begin{bmatrix} 3 & 0 & 1 \\ 0 & 1 & -1 \\ 5 & 4 & 2 \end{bmatrix} \\ \text{coefficient matrix} \end{array} \quad \text{and} \quad \begin{array}{c} \begin{bmatrix} 3 & 0 & 1 & 8 \\ 0 & 1 & -1 & 0 \\ 5 & 4 & 2 & 1 \end{bmatrix} \\ \text{augmented matrix} \end{array}.$$

- There are three *row operations* we can perform on a matrix: (1) add a multiple of one row to another row, (2) multiply a row by a *nonzero* number, (3) swap two rows. For example:

$$\begin{bmatrix} 0 & 0 \\ 1 & 2 \end{bmatrix} \xrightarrow{\text{row op. (1)}} \begin{bmatrix} 10 & 20 \\ 1 & 2 \end{bmatrix} \xrightarrow{\text{row op. (2)}} \begin{bmatrix} -5 & -10 \\ 1 & 2 \end{bmatrix} \xrightarrow{\text{row op. (3)}} \begin{bmatrix} 1 & 2 \\ -5 & -10 \end{bmatrix}.$$

Two matrices are *row equivalent* if one can be transformed to the other by row operations.

- Two linear systems (in the same variables, with the same number of equations) are equivalent (i.e., have same solutions) if their augmented matrices are row equivalent.

1 Introduction

Check the course website

<http://www.math.ust.hk/~emarberg/teaching/2019/Math2121/>

for the syllabus and other course details.

Each lecture corresponds to one or more sections in the textbook. Today's lecture corresponds to Section 1.1. For a more detailed discussion of the topics in any particular lecture, see the textbook.

Throughout, we'll be using the following notation:

- \mathbb{R} denotes the real numbers.
- \mathbb{Q} denotes the rational numbers p/q .
- \mathbb{Z} denotes the integers $\{\dots, -2, -1, 0, 1, 2, \dots\}$.
- \mathbb{N} denotes the nonnegative integers $\{0, 1, 2, \dots\}$.

Ellipsis (“...”) notation: we write a_1, a_2, \dots, a_7 instead of the full list $a_1, a_2, a_3, a_4, a_5, a_6, a_7$.

We use the same convention to write a_1, a_2, \dots, a_n even when n is a variable integer.

2 Systems of linear equations

Let x_1, x_2, \dots, x_n be variables, where $n \geq 1$ is some integer.

Let a_1, a_2, \dots, a_n, b be numbers in \mathbb{R} .

Unlike in calculus, where our favorite variables are x, y, z , in linear algebra we prefer x_1, x_2, x_3, \dots since later we will want to go beyond 3 dimensions.

Definition. We refer to

$$a_1x_1 + a_2x_2 + \dots + a_nx_n = b$$

as a *linear equation* in the variables x_1, x_2, \dots, x_n .

Notation. Another way of writing this equation is $\sum_{i=1}^n a_i x_i = b$.

The symbol “ \sum ” is the Greek letter sigma, for “sum.”

There are many other equivalent ways of writing the same equation. For example:

$$\begin{aligned} a_1x_1 + a_2x_2 + \dots + a_nx_n - b &= 0 \\ b &= a_1x_1 + a_2x_2 + \dots + a_nx_n \\ a_1x_1 + a_3x_3 + a_5x_5 + \dots &= b - a_2x_2 - a_4x_4 - \dots \end{aligned}$$

We consider all of these equations to be the same thing.

Example. The following are all linear equations:

$$3x_1 = 2x_2, \quad 3x_1 + \frac{4}{3}x_2 - \sqrt{2}x_3 = 7, \quad 0 = 0, \quad 0 = 1.$$

Even though the last two equations involve no variables, they have the form required of a linear equation. (The last equation is false, but a false equation is still an equation.)

The following are *not* linear equations:

$$3x_1^2 + 4x_2 = 7, \quad x_1x_2 = x_3, \quad \sqrt{x^2 - 1} = 2.$$

A *system of linear equations* or *linear system* is a list of linear equations.

Example.

$$\begin{aligned} 2x_1 - x_2 + \sqrt{3}x_3 &= 8 \\ x_1 - 4x_3 &= 8 \\ x_2 &= 0 \end{aligned}$$

is a linear system in the variables x_1, x_2, x_3 .

Definition. A *solution* of a linear system in variables x_1, x_2, \dots, x_n is a list of n numbers (s_1, s_2, \dots, s_n) with the property that if we set $x_1 = s_1, x_2 = s_2, \dots, x_n = s_n$ in our equations, we get all true statements.

If our system contains any false equations like “ $0 = 1$ ”, then it cannot have any solutions.

Two linear systems are *equivalent* if they have the same set of solutions.

Example. How many solutions can a linear system have?

1. The system

$$\begin{aligned} x_1 - 2x_2 &= -1 \\ -x_1 + 3x_2 &= 3 \end{aligned}$$

has one solution $(s_1, s_2) = (3, 2)$.

2. But the system

$$\begin{aligned} x_1 - 2x_2 &= -1 \\ 3x_1 - 6x_2 &= -3 \end{aligned}$$

has many solutions: $(s_1, s_2) = (1, 1)$ or $(3, 2)$ or $(5, 3)$ or \dots

3. Whereas the system

$$\begin{aligned} x_1 - 2x_2 &= -1 \\ x_1 - 2x_2 &= 0 \end{aligned}$$

has no solutions.

Theorem. A linear system in two variables x_1 and x_2 has either 0, 1, or infinitely many solutions.

Proof by geometry. A solution to one equation $ax_1 + bx_2 = c$ represents a point on a line after we identify the pair of numbers (x_1, x_2) with a point in the Cartesian plane.

A solution to a system of 2-variable linear equations represents a point where the lines defined by the equations all intersect.

But a collection of lines all intersect at either 0 points (they don't have a common intersection), 1 point (the unique point of intersection) or at infinitely many points (in the case when the lines are all *the same line*, though they might come from different equations). \square

Proof by algebra. Suppose the linear system has two different solutions (s_1, s_2) and (r_1, r_2) .

Define $\lambda_1 = s_1 - r_1$ and $\lambda_2 = s_2 - r_2$.

The symbol “ λ ” is the Greek letter lambda.

Then $(s_1 + z\lambda_1, s_2 + z\lambda_2)$ is a new solution to our system, for any choice of z .

To check this, suppose $ax_1 + bx_2 = c$ was one of the equations in our system. Then

$$a(s_1 + z\lambda_1) + b(s_2 + z\lambda_2) = (as_1 + bs_2) + z(a\lambda_1 + b\lambda_2).$$

On the right, the first term is $as_1 + bs_2 = c$, and the second term is zero since

$$a\lambda_1 + b\lambda_2 = as_1 - ar_1 + bs_2 - br_2 = (as_1 + bs_2) - (ar_1 + br_2) = c - c = 0.$$

Therefore $a(s_1 + z\lambda_1) + b(s_2 + z\lambda_2) = c + 0 = c$ so $(s_1 + z\lambda_1, s_2 + z\lambda_2)$ is indeed a solution.

Since z can be any number, the system has infinitely many solutions. \square

A linear system is *consistent* if it has one or infinitely many solutions, and *inconsistent* if it has zero solutions. Both the algebraic and geometric proofs generalize to any number of variables. (Think about how to do this!) Therefore:

Theorem. Any linear system in n variables is either consistent or inconsistent, and therefore has either 0, 1, or infinitely many solutions.

3 Matrices

A *matrix* is just a rectangular array of numbers, like these ones:

$$\begin{bmatrix} 1 \end{bmatrix} \quad \text{or} \quad \begin{bmatrix} 5 & 3 \\ 2 & \pi \end{bmatrix} \quad \text{or} \quad \begin{bmatrix} 7 & 6 & 4 & 3 \\ 2 & 1 & 1 & 0 \end{bmatrix}.$$

We denote a general matrix by

$$A = \begin{bmatrix} A_{11} & A_{12} & A_{13} & A_{14} \\ A_{21} & A_{22} & A_{23} & A_{24} \\ A_{31} & A_{32} & A_{33} & A_{34} \end{bmatrix}$$

Here “ A_{23} ” is pronounced “A, two, three”. This matrix is 3-by-4: it has 3 rows and 4 columns.

Say that a matrix A is m -by- n or $m \times n$ if has m rows and n columns.

We usually write A_{ij} (pronounced “A, i, j”) for the entry in the i th row and j th column of the matrix.

Matrices are useful as a compact way of writing a linear system.

Consider the linear system

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ 2x_2 - 8x_3 &= 8 \\ 5x_1 - 5x_3 &= 10 \end{aligned}$$

Define the *coefficient matrix* of this system to be

$$\begin{bmatrix} 1 & -2 & 1 \\ 0 & 2 & -8 \\ 5 & 0 & -1 \end{bmatrix}$$

In other words, the matrix A where A_{ij} is the coefficient of x_j in the i th equation.

The *augmented matrix* of the system is

$$\begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 2 & -8 & 8 \\ 5 & 0 & -1 & 10 \end{bmatrix}.$$

Exercise: how would you generalize this definition to any linear system?

4 Solving linear systems

We solve linear systems by adding equations together to cancel variables.

Example. To solve

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ 2x_2 - 8x_3 &= 8 \\ 5x_1 - 5x_3 &= 10 \end{aligned} \quad \begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 2 & -8 & 8 \\ 5 & 0 & -5 & 10 \end{bmatrix}$$

we first add -5 time equation 1 to equation 3 to get

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ 2x_2 - 8x_3 &= 8 \\ 10x_2 - 10x_3 &= 10 \end{aligned} \quad \begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 2 & -8 & 8 \\ 0 & 10 & -10 & 10 \end{bmatrix}.$$

We then multiply equation 2 by $1/2$ to get

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ x_2 - 4x_3 &= 4 \\ 10x_2 - 10x_3 &= 10 \end{aligned} \quad \begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 1 & -4 & 4 \\ 0 & 10 & -10 & 10 \end{bmatrix}.$$

We then add -10 times equation 2 to equation 3:

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ x_2 - 4x_3 &= 4 \\ 30x_3 &= -30 \end{aligned} \quad \begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 1 & -4 & 4 \\ 0 & 0 & 30 & -30 \end{bmatrix}.$$

Multiple equation 3 by $1/30$:

$$\begin{aligned} x_1 - 2x_2 + x_3 &= 0 \\ x_2 - 4x_3 &= 4 \\ x_3 &= -1 \end{aligned} \quad \begin{bmatrix} 1 & -2 & 1 & 0 \\ 0 & 1 & -4 & 4 \\ 0 & 0 & 1 & -1 \end{bmatrix}.$$

The augmented matrix of the last system is *triangular*: all entries in positions (i, j) with $i > j$ are zero.

Remember that i is the row, j is the column.

We can easily solve for x_1, x_2, x_3 from a triangular system, working from the bottom up:

- The last equation $x_3 = -1$ is already as simple as possible.
- Substitute into second equation: $x_2 - 4x_3 = x_2 - 4(-1) = 4 \Rightarrow x_2 = 0$.
- Substitute into first equation: $x_1 - 2x_2 + x_3 = x_1 - 2(0) + (-1) = 0 \Rightarrow x_1 = 1$.

Definition. In solving this system of equations, we performed the following (*elementary*) *row operations* on the augmented matrix of the system:

1. Replacement: replace one row by the sum of itself and a multiple of another row.
2. Scaling: multiple all entries in a row by a *nonzero* number.
3. Interchange: swap two rows.

Note: we “add” rows by adding the corresponding entries:

$$\begin{bmatrix} 1 & 2 & 3 & 4 \end{bmatrix} + \sqrt{7} \begin{bmatrix} 0 & 8 & 4 & 6 \end{bmatrix} = \begin{bmatrix} 1 & 2 + 8\sqrt{7} & 3 + 4\sqrt{7} & 4 + 6\sqrt{7} \end{bmatrix}.$$

Two matrices are *row equivalent* if one can be transformed to the other by a sequence of row operations.

Each row operation is reversible. (Exercise: why?)

Theorem. If the augmented matrices of two linear systems are row equivalent, then the systems are equivalent (i.e., have same solutions).

Proof. Here's the idea, minus the details: check that performing one row operation does not change whether a given (s_1, s_2, \dots, s_n) is a solution to the linear system. \square

Given a linear system with augmented matrix A , suppose we perform row operations on A until we get a matrix T with the property that whenever T_{ij} is the first nonzero entry in the i th row of T going left to right, then T_{ij} is the last nonzero entry in the j th column of T going top to bottom. For example:

$$T = \begin{bmatrix} 1 & 6 & 8 & 9 & 0 \\ 0 & 0 & 3 & 2 & 1 \\ 0 & 0 & 0 & 4 & 2 \end{bmatrix} \quad \text{or} \quad T = \begin{bmatrix} 1 & 6 & 8 & 9 & 0 \\ 0 & 0 & 3 & 2 & 1 \\ 0 & 0 & 0 & 0 & 2 \end{bmatrix}$$

From T in this form, we can easily determine if the system we started out with is consistent or inconsistent.

If T is the left matrix, the system is consistent: we have

$$x_4 = 4, \quad 3x_3 + 2x_4 = 1, \quad \text{and} \quad x_1 + 6x_2 + 8x_3 + 9x_4 = 0.$$

Exercise: find a solution!

If T is the right matrix, the system is inconsistent: it includes the equation $0 = 2$, from the last row.

In general, a linear system is inconsistent if and only if its augmented matrix can be transformed by row operations to a matrix with a row of the form

$$[0 \ 0 \ \dots \ 0 \ q]$$

where $q \neq 0$. We'll prove this next time, after introducing the course's most important algorithm, *row reduction to echelon form*.

5 Vocabulary

Keywords from today's lecture:

1. Linear equation.

An equation of the form $a_1x_1 + a_2x_2 + \dots + a_nx_n = b$ where n is a positive integer, a_1, a_2, \dots, a_n, b are numbers, and x_1, x_2, \dots, x_n are variables.

Example: $3x_1 - \frac{1}{7}x_3 = x_4 + 5$.

2. Linear system or system of linear equations.

A list of one or more linear equations.

Example:
$$\begin{cases} x_1 + x_2 = 3 \\ 3x_2 - x_1 = 2 \end{cases}$$

3. Solution to a linear system.

A solution to one linear equation $a_1x_1 + a_2x_2 + \dots + a_nx_n = b$ is a list of numbers (s_1, s_2, \dots, s_n) such that $a_1s_1 + a_2s_2 + \dots + a_ns_n$ is equal to b . A solution to a linear system is a list of numbers that is simultaneously a solution to every equation in the system.

Example: a solution to
$$\begin{cases} x_1 + x_2 = 3 \\ 3x_2 - x_1 = 2 \end{cases}$$
 is $(s_1, s_2) = (\frac{7}{4}, \frac{5}{4})$.

4. Equivalent linear systems.

Two linear systems with the same sets of variables and same sets of solutions.

Example:
$$\begin{cases} x_1 + x_2 = 3 \\ 3x_2 - x_1 = 2 \end{cases} \quad \text{and} \quad \begin{cases} 2x_1 + 2x_2 = 6 \\ x_1 - 3x_2 + 2 = 0 \end{cases} \quad \text{are equivalent.}$$

5. Consistent linear system.

A linear system with at least one solution.

Example:
$$\begin{cases} x_1 + x_2 = 3 \\ 3x_2 - x_1 = 2 \end{cases}$$
 is consistent.

6. Inconsistent linear system.

A linear system with no solutions.

Example:
$$\begin{cases} x_1 + x_2 = 3 \\ 2x_1 + 2x_2 = 4 \end{cases}$$
 is inconsistent.

7. Matrix.

A rectangular array of numbers. A matrix A is $m \times n$ if it has m rows and n columns.

We write A_{ij} for the entry of A in row i and column j .

Example: $A = \begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix}$. This matrix is 2×3 and $A_{21} = \sqrt{2}$ while $A_{12} = -1$.

8. **Coefficient matrix** of a linear system.

For a linear system m equations with n variables, the $m \times n$ matrix that records the coefficients of the variables.

Example: $\begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix}$ is the coefficient matrix of $\begin{cases} -x_2 + 2x_3 = 3 \\ \sqrt{2}x_1 + 5x_2 + 6x_3 = 7 \end{cases}$.

9. **Augmented matrix** of a linear system.

For a linear system m equations with n variables, the $m \times (n+1)$ matrix that records the coefficients of the variables and the constant on the other side of each equation.

Example: $\begin{bmatrix} 0 & -1 & 2 & 3 \\ \sqrt{2} & 5 & 6 & 7 \end{bmatrix}$ is the augmented matrix of $\begin{cases} -x_2 + 2x_3 = 3 \\ \sqrt{2}x_1 + 5x_2 + 6x_3 = 7 \end{cases}$.

10. **Elementary row operator** on a matrix.

One of the following operations on a matrix: replace one row by the sum of the row and a multiple of another row, multiply all entries in row by a fixed number, or swap two rows.

Example: $\begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix} \rightarrow \begin{bmatrix} 2\sqrt{2} & 9 & 14 \\ \sqrt{2} & 5 & 6 \end{bmatrix}$

Example: $\begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix} \rightarrow \begin{bmatrix} 0 & -1 & 2 \\ 5\sqrt{2} & 25 & 30 \end{bmatrix}$

Example: $\begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix} \rightarrow \begin{bmatrix} \sqrt{2} & 5 & 6 \\ 0 & -1 & 2 \end{bmatrix}$.

11. **Row equivalent matrices**.

Matrices that can be transformed to each other by a sequence of row operations.

Example: $\begin{bmatrix} 0 & -1 & 2 \\ \sqrt{2} & 5 & 6 \end{bmatrix} \rightarrow \begin{bmatrix} 2\sqrt{2} & 9 & 14 \\ \sqrt{2} & 5 & 6 \end{bmatrix} \rightarrow \begin{bmatrix} 2\sqrt{2} & 9 & 14 \\ 5\sqrt{2} & 25 & 30 \end{bmatrix} \rightarrow \begin{bmatrix} 5\sqrt{2} & 25 & 30 \\ 2\sqrt{2} & 9 & 14 \end{bmatrix}$